

V7-RUB6

V7 Option Switch Settings: 1 (Special Pulse/ICT004/MDB)

Supported bill Ruble 5, 10, 50, 100, 200, 500 6bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★ Reject Ruble 5 (Note 1.)	ON							
★ Accept Ruble 5 (Note 1.)	OFF							
★ Reject Ruble 10		ON						
★ Accept Ruble 10		OFF						
★ Reject Ruble 50 & 100			ON					
★ Accept Ruble 50 & 100			OFF					
★ Reject Ruble 200				ON				
★ Accept Ruble 200				OFF				
★ Reject Ruble 500					ON			
★ Accept Ruble 500					OFF			
★ Reserved						ON		
★ Reserved						OFF		
★ Harness Disable							ON	
★ Harness Enable							OFF	
★ Inhibit Active High								ON
★ Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ 1 pulse / Ruble 5	OFF	OFF		
2 pulses / Ruble 5	ON	OFF		
5 pulses / Ruble 5	OFF	ON		
10 pulses / Ruble 5	ON	ON		
★ 50ms LO / 50ms HI			OFF	OFF
60ms LO / 300ms HI			ON	OFF
30ms LO / 50ms HI			OFF	ON
150ms LO / 150ms HI			ON	ON

★ Manufacture setting

V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ 1 pulse / Ruble 10	OFF	OFF		
2 pulses / Ruble 10	ON	OFF		
5 pulses / Ruble 10	OFF	ON		
10 pulses / Ruble 10	ON	ON		
★ 50ms LO / 50ms HI			OFF	OFF
60ms LO / 300ms HI			ON	OFF
30ms LO / 50ms HI			OFF	ON
150ms LO / 150ms HI			ON	ON

★ Manufacture setting

V7-RUB6(Special Pulse/ICT004/MDB)

V7 Interface Settings: 3 (ICT004)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
★ Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	Ruble 10	Ruble 10	Ruble 10
BV2	Ruble 50	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100
BV4	Ruble 200	Ruble 200	Ruble 200
BV5	Ruble 500	Ruble 500	Ruble 500
BV6	Ruble 5	Ruble 5	Ruble 5

Note: (1) Dip Switch 1 is for Pulse.

When SW1 Dip1 is OFF(Accept 5 Rubles),

Pulse → 5 Rubles=1 Pulse, 10 Rubles=2 Pulse, 50 Rubles=10 Pulse,
100 Rubles=20 Pulse, 200 Rubles=40 Pulse, 500 Rubles=100 Pulse.

When SW1 Dip1 is ON(Reject 5 Rubles),

Pulse → 10 Rubles=1 Pulse, 50 Rubles=5 Pulse, 100 Rubles=10 Pulse,
200 Rubles=20 Pulse, 500 Rubles=50 Pulse.