

Date of sending : 2023.12.15 Filename : 724yXRUF1(V3.06_CCCC).BIN
 Rom-ID : 724yXRUF1(V3.06_CCCC)
 Type : V7
 System(Control) : 724
 Device(Protocol): yX (Special Pulse+ICT004+M.D.B_US)
 Online Upgrade : None
 MDB Version : 4.2 (Software Version: 3.06)
 Judgement(Notes): RUF1
 Checksum : CCCC
 Currency : RUR
 Accepted notes : 5(1997)
 10(2001~2004) 、
 50(2001~2004) 、
 100(Old 2001~2004,New 2022) 、
 200(2017) 、
 500(Old 2001~2004,New 2010) (6 bills)
 Accepted ways : 4

Dip switch settings:

 1 ON : Reject 5 Rubles (NOTE.1)
 * OFF: Accept 5 Rubles (NOTE.1)

 2 ON : Reject 10 Rubles
 * OFF: Accept 10 Rubles

 3 ON : Reject 50 & 100 Rubles
 * OFF: Accept 50 & 100 Rubles

 4 ON : Reject 200 Rubles
 * OFF: Accept 200 Rubles

 5 ON : Reject 500 Rubles
 * OFF: Accept 500 Rubles

 6 ON : Reserved
 * OFF: Reserved

 ON : Harness Disable
 7 * OFF: Harness Enable

 ON : Inhibit Active High
 8 * OFF: Inhibit Active Low

ICT004 Interface	Pulse Mode					MDB Mode
SW2	SW2					SW2
1 ON : Reserved	1 *OFF	ON	OFF	ON		1 ON : Reserved
OFF: Reserved	2 *OFF	OFF	ON	ON		OFF: Reserved
-----						-----

724yXRUF1(V3.06_CCCC).txt									
2	ON : Reserved OFF: Reserved	1 Pulse 1 Pulse	2 Pulses 2 Pulses	5 Pulses 5 Pulses	10 Pulses / 5 Rubles (NOTE.1) 10 Pulses /10 Rubles (NOTE.1)	2	ON : Reserved OFF: Reserved		
3	ON : Reserved OFF: Reserved	3 *OFF 4 *OFF	ON OFF	OFF ON	ON ON	3	ON : Reserved OFF: Reserved		
4	ON : Reserved OFF: Reserved	50ms Lo 50ms Hi	60ms Lo 300ms Hi	30ms Lo 50ms Hi	150ms Lo 150ms Hi	4	ON : Reserved OFF: Reserved		
SW3 (internal)		SW3 (internal)				SW3 (internal)			
1	ON : Reserved * OFF: Reserved	1 * ON : Credit-Pulse Normal HIGH OFF: Credit-Pulse Normal LOW				1 * ON: Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 OFF : Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0			
2	OFF	2	ON			2	OFF		
3	ON ->ICT004 Interface(**)	3	OFF ->Pulse Interface(**)			3	OFF ->MDB Interface(**)		
4	ON : Reserved * OFF : Reserved	4	ON : Reserved * OFF : Reserved			4	ON : Reserved * OFF : Reserved		

NOTE @

- (1) Dip Switch 1 is for Pulse
 When SW1 Dip1 is OFF(Accept 5 Rubles),
 Pulse==>5 Rubles=1 Pulse,10 Rubles=2 Pulse,50 Rubles=10 Pulse,100 Rubles=20 Pulse,200 Rubles=40 Pulse,500 Rubles=100 Pulse.
 When SW1 Dip1 is ON (Reject 5 Rubles),
 Pulse==>10 Rubles=1 Pulse,50 Rubles=5 Pulse,100 Rubles=10 Pulse,200 Rubles=20 Pulse,500 Rubles=50 Pulse.

CURRENCY ASSIGN DATA (RUB)			
	ICT004	Pulse	MDB
BV1	Rubles 10	Rubles 10	Rubles 10
BV2	Rubles 50	Rubles 50	Rubles 50
BV3	Rubles 100	Rubles 100	Rubles 100
BV4	Rubles 200	Rubles 200	Rubles 200
BV5	Rubles 500	Rubles 500	Rubles 500
BV6	Rubles 5	Rubles 5	Rubles 5

Bezel LED & Back LED lights display list:

1.Bill Acceptor in the idle state Bezel LED display:

Setting	Display

	Colorful light.
	The blue light flashes.
*	The green light flashes.
	No light.

2.Bezel LED Errors:

Green	Status
1	White Card Calibration.

3.Back LED Errors:

LED Flashes	Status
Green	
1	Bill Jammed.
2	Disable.
3	Recognition sensor error.
3+2	Hook sensor error.
3+5	Magnetic Head error.
(Optional)	
4	Anti-string sensor error or A stringing attempt has detected.
5	Bill box has been removed.
6	Stacker error or stacker full.
7	Motor error.